



## SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A



Product designation				Soft Starter
Product type designation	า			ADX
Motor type				Asynchronous
				three phase
Electrical features				
Supplies voltage				
		Type of system		Three phase
		Rated supply voltage	V	208415VAC
		auxiliary supply voltage (Us)		208240VAC
-		Rated frequency	Hz	50/60
Rated starter current le			Α	310
Rated motor power				
	IEC ratings (T≤40°C)			
		230VAC	kW	90
		400VAC	kW	160
<u>-</u>		500VAC	KW	200
	UL ratings (T≤40°C)			
		220-240VAC	HP	100
		380-415VAC	HP	150
		440-480VAC	HP	250
Number of controlled ph	2928		Nr.	3
Transci of controlled pri	4303			
·	4000			No, predisposed
Built-in bypass	4000			No, predisposed for external
Built-in bypass				No, predisposed for external bypass contactor
Built-in bypass Cooling System				No, predisposed for external
Built-in bypass				No, predisposed for external bypass contactor Forced
Built-in bypass  Cooling System  Programming interface				No, predisposed for external bypass contactor Forced  Backlit LCD 2x16
Built-in bypass  Cooling System  Programming interface  Display				No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to				No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to Optical port	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to Optical port  Startup and stop settings	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No Torque or voltage
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to Optical port	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No Torque or voltage ramp with current
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to Optical port  Startup and stop settings	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character  No  No  Torque or voltage ramp with current limitation
Built-in bypass  Cooling System Programming interface Display  Programming with NFC to Optical port Startup and stop settings Startup method	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No  Torque or voltage ramp with current limitation Torque ramp,
Built-in bypass  Cooling System  Programming interface  Display  Programming with NFC to Optical port  Startup and stop settings	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character  No  No  Torque or voltage ramp with current limitation  Torque ramp, voltage ramp,
Built-in bypass  Cooling System Programming interface Display  Programming with NFC to Optical port Startup and stop settings Startup method  Stop method	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No Torque or voltage ramp with current limitation Torque ramp, voltage ramp, free-wheel stop
Built-in bypass  Cooling System Programming interface Display  Programming with NFC to Optical port Startup and stop settings Startup method	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character  No  No  Torque or voltage ramp with current limitation  Torque ramp, voltage ramp, free-wheel stop  DC dynamic with
Built-in bypass  Cooling System Programming interface Display Programming with NFC to Optical port Startup and stop settings Startup method  Stop method  Braking method	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character No No Torque or voltage ramp with current limitation Torque ramp, voltage ramp, free-wheel stop
Built-in bypass  Cooling System Programming interface Display  Programming with NFC to Optical port Startup and stop settings Startup method  Stop method	technology			No, predisposed for external bypass contactor Forced  Backlit LCD 2x16 character  No  No  Torque or voltage ramp with current limitation  Torque ramp, voltage ramp, free-wheel stop  DC dynamic with





# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A

Power supply Protection	No power, phase loss, phase sequence, frequency out of limits, minimum and maximum voltage
Motor protection	Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run), overtemperature, starting too long Overcurrent,
Starter protection	overcurrent, overtemperature, bypass failure, phase shorted, temperature sensor fault, maintenance request
Functions	
Built-in bypass	No
Built-in display and keypad	No
Languages	4
View measurements	Yes
Torque control	Yes
	. 55
Adjustable current limit	Yes
Dynamic braking	Yes Yes
Dynamic braking Kick Start function	Yes Yes Yes
Dynamic braking Kick Start function Motor overload electronic protection	Yes Yes Yes Yes Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input	Yes Yes Yes Yes Yes Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss	Yes Yes Yes Yes Yes Yes Yes Yes Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs Analog inputs	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs Analog inputs Digital outputs	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs Analog inputs Digital outputs Analog output	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs Analog inputs Digital outputs Analog output Monitoring communication	Yes
Dynamic braking Kick Start function Motor overload electronic protection Motor protection PTC input Protection against phase loss Protection against phase inversion Protection against locked rotor Protection against thyristor overtemperature Protection against low load Programmable alarm Digital inputs Analog inputs Digital outputs Analog output	Yes





## SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A

Startup counter			Yes
Clock calendar			Yes
Remote external keypad			Yes
Input and Output			
Digital inputs			0 (0 11 11 11
	Number of digital input	Nr.	3 (2 digital inputs + 1 digital/analog input) 24VDC (no need
	Digital input type  Digital input functions		24VDC (no need for external feeder) 1 input for start, a input programmable (stop, free-wheel stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second motor), 1 input programmable multifunction (OFF, free-wheel stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second motor, cascade starting, 0-10V ramp, 2-10V ramp, 0-10V start-stop, PT100 start-stop, PTC protection)
Analog inputs	Number of analog input	Nr.	1 (digital/analog) 0-10VDC (0-
	Analog input type		20mA with external resistor 500Ω)





## SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A


Analog input functions		Motor protection via PTC probes, acceleration and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable and disable, PT100 input thresholds for motor starting and stopping and PT100 input thresholds for programmable relay enable and disable relay enable and disable
Digital outputs  Number of digital output	Nr.	4
Digital output arrangement		3 x 1 NO (SPST) + 1 C/O (SPDT) Ratings: 5A 250VAC AC1, 2A 250VAC AC15
Digital output functions		C/O output for global alarm, 3 x 1NO outputs programmable (OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx)
Analog outputs  Number of analog output	Nr.	1
Analog output type		020mA, 420mA (010V with external resistor 500Ω)
Analog output functions  Ambient conditions		Current, torque, motor thermal status, power factor and active power
Temperature		
Operating temperature min	°C	-10





# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A

	max	°C	+55°C (with current derating >45°C of 1.5%/°C)
Storage temperature			
	min	°C	-30
	max	°C	+70
Max altitude		m	1000 without derating (over 1000mt with current derating of 0.5%/100m)
Relative humidity		%	95% without condensation or dripping
Pollution degree			3
Housing			
Mounting			Screw-fixing
IP degree of protection			IP00
Dimensions (W x H x D)		mm	640 x 600 x 380
Weight		Kg	48.9
Dimensions			



TYPE	Α	В	C	D	E	F
ADX 0310	640 (25.20")	600 (23.62")	380 (14.96")	620 (24.41")	400 (15.75")	100 (3.94")
ADX 0365	640 (25.20")	600 (23.62")	380 (14.96")	620 (24.41")	400 (15.75")	100 (3.94")
ADX 0470	790 (31.10")	650 (25.59")	430 (16.93")	770 (30.31")	450 (17.72")	100 (3.94")
ADX 0568	790 (31.10")	650 (25.59")	430 (16.93")	770 (30.31")	450 (17.72")	100 (3.94")
ADX 0640	790 (31.10")	650 (25.59")	430 (16.93")	770 (30.31")	450 (17.72")	100 (3.94")
ADX 0820	910 (35.83")	950 (37.40")	442 (17.40")	830 (32.68")	920 (36.22")	0
ADX 1200	910 (35.83")	950 (37.40")	442 (17.40")	830 (32.68")	920 (36.22")	0

<sup>•</sup> Consult Customer Service; see contact details on inside front cover.





SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). PREDISPOSED FOR EXTERNAL BY-PASS CONTACTOR, 310A

Certifications and co	mpliance
Compliance	
	IEC/EN 60947-1
	IEC/EN 60947-4-2
Certificates	
	EAC
ETIM classification	

ETIM 8.0

starter

EC000640 - Soft